




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : A61B 5/12, 1/227	A1	(11) International Publication Number: WO 98/23205 (43) International Publication Date: 4 June 1998 (04.06.98)
(21) International Application Number: PCT/US97/21420 (22) International Filing Date: 25 November 1997 (25.11.97) (30) Priority Data: 60/032,030 25 November 1996 (25.11.96) US (71) Applicant: MDI INSTRUMENTS, INC. [US/US]; Suite 2850, 600 West Cummings Park, Woburn, MA 01801-6397 (US). (72) Inventor: BRAINARD, Edward, C., II; 23 Rogers Drive, Marion, MA 02738 (US). (74) Agent: GORDON, Peter, J.; Wolf, Greenfield & Sacks, P.C., 600 Atlantic Avenue, Boston, MA 02210 (US).		(81) Designated States: AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GE, GH, HU, ID, IL, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, UA, UG, UZ, VN, YU, ZW, ARIPO patent (GH, KE, LS, MW, SD, SZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, ML, MR, NE, SN, TD, TG). Published <i>With international search report. Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i>

(54) Title: INNER EAR DIAGNOSTIC APPARATUS AND METHOD

(57) Abstract

A system and method for measurement of ear conditions utilizing a test signal. The apparatus includes a wave guide (16) having a proximal and distal end. The distal end is connected to a probe tip (18), which may be fabricated of a semi-rigid material or rigid material and may further be a material transmissive light. The probe tip (18) is sized so as to fit at least a portion of the probe tip (18) within the ear canal (38). The wave guide (16) further includes an acoustic energy source (14) disposed substantially at the proximal end for generating a test acoustic wave in response to a source signal. The wave guide (16) further includes an acoustic energy detector, for example a microphone (20), for detection of reflected acoustic energy and generation of an electrical signal in response. The apparatus is controlled by a processor. The processor is adapted to generate the source signal which will preferably contain pseudo-random noise. The processor is further adapted to receive the detected signal from the acoustic energy detector and to generate a condition signal related to the ear condition in response to the detector signal and the source signal. The condition signal may be utilized to control a video display (43), a printout device (44), or any other device capable of conveying to the operator the ear condition. The apparatus may be further adapted to view the ear while testing by including a lens (22) at the proximal end and a light source (24) toward the distal end of the wave guide (16). Also disclosed is a method for measurement of ear conditions.



FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon		Republic of Korea	PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakhstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

INNER EAR DIAGNOSTIC APPARATUS AND METHOD

Cross-Reference to Related Application

This application claims is related to U.S. patent application serial no. 60/032.030, filed
5 November 25, 1996, which is hereby incorporated by reference.

Background of the Invention

This invention relates to an apparatus for testing and evaluating an individual's capacity
to hear and more particularly to an apparatus to monitor middle ear effusion and other ear
10 abnormalities in infants, children and adults.

There are a number of diagnostic tests based upon the use of probes placed within ears to
deliver tones and measure the function of the ear elements on a non-contact basis. One method
for testing and evaluating auditory responses is impedance audiometry. This method uses
acoustical measurements made within the test subject's ear canal. A known acoustic test signal
15 having a predefined frequency is inserted into the ear canal and allowed to propagate to the
tympanic membrane. A sensor measures the signal reflected back from the membrane. The
impedance of the inner ear is thus computed by comparing the test signal with the reflected
signal.

Prior impedance audiometry systems relied on a test probe that sealed to the ear canal,
20 creating a sealed chamber and an air source for selectively pressurizing the chamber. The
pressure present in the chamber prestresses the tympanic membrane. At each of a variety of
known chamber pressures, these systems would insert the test signal into the ear canal and
measure the reflected signal. In this way the inner ear would be characterized by the reflected
signals for each of the predetermined pressures.

25 These prior impedance audiometry systems suffered from a variety of shortcomings.
Since the systems require the formation of a sealed chamber between the test probe and the
tympanic membrane, the test probe must be adaptable to closely fit a variety of ear canal sizes.
In addition, since the system requires the chamber to be pressurized to a pressure value different
from atmospheric pressure, the subject can suffer discomfort during testing.

30 Other diagnostic tests utilize acoustic reflectometry, a test method in which the tool
sweeps a range of frequencies at atmospheric pressure without a seal to the ear. The signal
reflected from the ear is analyzed and used to generate a test result indicative of the ear
condition. The disadvantage with this test method is that measurement of the reflected signal

maybe inaccurate due to poor acoustic reflection. In addition, alignment may be off, further degrading instrument performance.

Summary of the Invention

5 The present invention is an apparatus or method for detection of ear conditions. In one aspect of the invention, the apparatus includes a wave guide having a proximal and distal end. The distal end is connected to a probe tip, which may be fabricated of a semi-rigid material or rigid material and may further be a material transmissive to light. The probe tip is sized so as to fit at least a portion of the probe tip within the ear canal. In use, the tip may form a seal with the
10 ear canal. The wave guide further includes an acoustic energy source disposed substantially at the proximal end for generating a test acoustic wave in response to a source signal. The wave guide further includes an acoustic energy detector, for example a microphone, for detection of reflected acoustic energy and generation of an electrical signal in response.

 The apparatus is controlled by a processor. The processor is adapted to generate the
15 source signal which will preferably contain pseudo-random noise. The processor is further adapted to receive the detected signal from the acoustic energy detector and to generate a condition signal related to the ear condition in response to the detected signal and the source signal. The condition signal may be utilized to control a video display, a printout device, or any other device capable of conveying to the operator the ear condition.

20 Another aspect of the invention is an apparatus adapted to view the ear while testing using acoustic reflectance. The apparatus may include a lens at the proximal end and a light source toward the distal end of the wave guide. The light source illuminates the ear canal and tympanic membrane either by direct illumination or by transmission of light via the light transmissive probe tip. The lens focuses the light for the operator.

25 Another aspect of the invention is a probe tip for an acoustic reflectometer. the probe tip may have the portion disposed within the ear canal and have a substantially tapered cross-section. This allows the use of single probe tip over a variety of ear canal sizes.

 The apparatus may be contained in a single, hand-held portable device. Alternatively, the processor, display devices and power source may be external to the housing.

Brief Description of the Drawings

A preferred embodiment of the invention has been chosen for purposes of illustration and description and is shown in the accompanying drawings, forming a part of the specification, wherein:

5 FIG. 1 is a cross-sectional view of an embodiment of the present invention;

FIG. 2 is a block diagram of the major components of an embodiment of the present invention;

FIG. 3 are graphs illustrating the acoustic measurements utilizing a method of the present invention and indicates the typical response for a normal child ear;

10 FIG. 3a is a cross-sectional view of the an embodiment of the present invention indicating the dimensions of a portion of the probe assembly;

FIG. 3b shows cross-sectional views of a variety of embodiments for the probe tip of the present invention;

15 FIG. 3c is a cross-sectional view of an additional embodiment for the probe tip of the present invention;

FIG. 3d shows cross-sectional views of additional embodiments for the probe tip of the present invention;

FIG. 3e is a graph illustrating the third-octave averaged energy reflectance versus center frequency (Hz) for adult group and infants of ages 1, 3, 6, 12 and 24 months;

20 FIG. 3f is a table disclosing initial MLSSA parameters.

FIG. 4 is a graph illustrating the computer model output for an embodiment of the present invention;

FIG. 5 are graphs illustrating the measurements of a variety of healthy ears in response to a test method of the present invention;

25 FIG. 6 are graphs illustrating the response of a child ear having an abnormal condition in response to a test method of the present invention;

FIG. 7 are graphs illustrating the response of the child ear of FIG. 6 after removing the typical response formed from the measurements illustrated in FIG. 5; and

30 FIG. 8 are graphs illustrating the response of a child ear having a conductive hearing loss condition in response to a test method of the present invention.

Detailed Description of the Preferred Embodiment

The present invention is an instrument and method that provides information about the function and integrity of the ear. The instrument monitors middle ear effusion and other ear abnormalities in infants, children and adults. It uses a test probe which couples to the ear at atmospheric pressure and delivers a known test signal.

FIG. 1 illustrates a cross-sectional view of an embodiment of the present invention. The instrument comprises a housing 10 sized to be held by the clinician. The housing 10 contains a switch 12 for operation of the instrument by the clinician. The switch 12 is adapted to actuate the instrument, wherein a test signal generated by sound source 14 is carried via wave guide 16 to probe tip 18. Probe tip 18 is sized appropriately to fit the test subject. Microphone 20 measures the reflected signal received back from the test subject via probe tip 18 and wave guide 16.

The housing also optionally may include a lens 22 for the clinician to utilize to examine the subject's tympanic membrane. The light source 24 may be positioned as needed and may provide direct illumination, or alternatively, may provide indirect illumination that is then carried to the wave guide 16 via optical fiber 26. Housing 10 also may hold the electronics for performing signal analysis. As an alternative, the control electronics may be exterior to the housing 10 with the control signal for the sound source 14 and the signal detected by the microphone 20 provided externally via wires or optical fibers.

FIG. 2 illustrates a block diagram for an embodiment of the present invention. The system utilizes a computer 30 which may be a digital microcomputer or analog computer. The computer 30 is adapted to control a signal generator 32 to create a test signal. The test signal is preferably pseudo-random noise. The test signal is provided to a power amplifier 34 which amplifies and conditions the signal properly for sound source 14. The sound source 14 creates acoustical energy in response to the input signal. The sound source 14 is placed within the wave guide 16 so that the acoustic energy is passed through the wave guide into the ear canal 36 and onto the tympanic membrane 38. In response to the acoustic energy, a wave is reflected from the tympanic membrane 38 back through the ear canal 38 and into the wave guide 16. This reflected wave is detected by microphone 20 and, in response to the detected reflected wave, generates a signal. The signal is passed through an amplifier 40 and back to the computer 30 through a data acquisition circuit 41 for analysis. The device is first operated in air, the results of which are then subtracted from subsequent readings to provide zeroing at all frequencies.

The computer 30 is further adapted to perform signal analysis on the reflected wave signal with the respect to test signal. For instance, as illustrated, a Fourier Transform function 42 may be performed on the reflected wave signal and plotted on a hard copy device 44 or display on a screen 43. Other forms of signal analysis are possible and known in the art.

5 The graphs of FIG. 3 illustrate a typical response from a subject after the instrument has been zeroed in air without any further processing.

FIG. 3b illustrates the design and sizes for a variety of probe tips 18. FIG. 3c illustrates an alternative embodiment of the probe tip 18 wherein the probe tip 18 is designed to be used for a variety of ear canal diameters.

10 The outside diameter of the tip 18 is selected to penetrate into the ear of a subject and provide an airtight seal so that the instrument and ear canal will be sealed at atmospheric pressure. Thus the unit operates by forming a resonant closed end traveling wave tube to provide greatest selectivity and noise rejection. Typical Q for the system is four. This calculation is derived in the following way:

15 Q of a tuned circuit is $Q = \frac{X}{R}$, where Q = quality factor, X = reactance of either coil or capacitor in ohms, and R = series resistance in ohms.

$$Q = \frac{2\pi (\text{Energy stored /cycle})}{(\text{Energy dissipated/cycle})}$$

20 Bandwidth -3dB = $\frac{f_0}{Q}$ and $Q = \frac{f_0}{2\Delta f(-3dB)}$, where

f_0 = the resonant frequency, and

Q = the circuit Q.

25 High Q means higher selectivity and elimination of noise.

Resistance on the equivalent circuit reduces Q.

Given $f_0 = 2600$ Hz, and

$f_H = 2850$ Hz, and

$f_L = 2200$ Hz, then $\Delta f = 2850 - 2200 = 650$.

30 Therefore, $Q = \frac{f_0}{\Delta f} = \frac{2600}{650} = 4$.

Two different tip sizes are required to monitor from infants to grown children. The tips are designed so that a characteristic acoustic signature is detected by the instrument to allow
35 automatic calibration adjustment for different tips.

The instrument design has been assisted by utilizing a computer model which allows evaluation of different designs for the optimization of the instrument. An acoustic model which is sold under the name of AkAbak by Panzer and Partner of Munich, Germany has been utilized. The instrument, ear canal and tympanum have been modeled as three separate acoustic entities, namely 1) lens to microphone, 2) microphone to end of tip and 3) end of tip to the tympanum including the ear canal. The graphs of FIG. 4 show a typical output from a model. The dotted curve is for the instrument when it is operated in air not sealed to the ear. The solid line is for the output when it is operated sealed to the ear. The difference in the outputs shown in the shaded areas is the response when the instrument is operated after zeroing in air. The objective is to construct the instrument to have as much difference in response between the two conditions as possible which will provide the greatest sensitivity for detecting ear abnormalities.

With reference to FIG. 1, the interior of the acoustic section of the instrument, wave guide 16 and probe tip 18, is a straight tube which is blocked off at the end away from the ear canal with a lens 22. The probe tip 18 is made of a transparent clear material which will easily transmit light. The light source 24, such as a grain of wheat light or a krypton mini lamp, is mounted in the front of the instrument so that its light will be directed onto the clear tip 18. The tip 18 transmits the light into the ear canal 36 and, in combination with the lens 22, provides a convenient and inexpensive means to view the ear canal 36 and tympanic membrane 38. The feature may ensure that there is no blockage of the acoustic energy which is projected into the ear, and that the ear canal 36 is straightened to allow for the unimpeded resonance of the ear canal 36, tympanic membrane 38 and the instrument.

FIG. 3a illustrates an embodiment for the portion of the housing assembly for the instrument and gives measurements for the spacing of the earphone (Acoustic Driver) 14, microscope 20 and probe tip 18. The lens 22 is mounted at the right end of this assembly. As noted, FIG 3b shows a series of probe tip 18 designs used in the instrument. The two tips at the right hand of the drawing have worked the best since they seal in the ear canal with a good seal. The tips are made of acrylic or any other rigid and clear plastic which will transmit light. The assembly may protected with a protective covering.

FIG. 3c is a diagram of a probe tip 18 which is capable of fitting ear canals of individuals of all ages, from neonate to older child. It is the conical shape in the upper part of the drawing. FIG. 3c further contains the dimensions for ear canals from 1 month of age to adults. The dimensions for children seem to follow a proportionally progressive deepening and widening

with age, thus, the distance of the instrument assembly housing to the tympanum is constant for all ages using the same tip. As a result, the resonant frequency of the total traveling wave tube will be the same for all ages. This frequency has been selected to be in the range of 2100 Hz since the ear absorbs most sound energy in this frequency range and pathologies of the ear are most easily detected at these frequencies. For example, the following table illustrates the relationships of age, and the frequency at which maximum absorption occurs:

Age	Null Frequency (Hz)	Average Energy Reflectance (%)
1 mo.	2000	.105
3 mo.	2000	.120
6 mo.	2500	.130
12 mo.	4000	.160
24 mo.	3000	.120
Adult	3000	.350

FIG. 3d shows additional embodiments of tips and their dimensions.

FIG. 3e shows the null obtained when monitoring ears of children to adults for acoustic reflection. Designing an instrument to operate in this null region will function well but it is desirable to use the lowest frequency to have an instrument of suitable length for both the acoustic and optical requirements of the application.

The acoustic driver 14 is preferably located adjacent to the lens 22. The acoustic input to the driver 14 may be pseudo-random series of pulses, commonly referred to as a Maximum Length Sequence (MLS), created either in software or using a hard wire shift register and XOR gate driven by clock pulses. The square wave pulses are selected to generate the acoustic frequencies between 100 to 10,000 Hz. The reception rate, pulse length, number of pulses, and spacing can be selected to fit the design of the unit and meet certain established criteria of frequency domain analysis for desired lowest frequency, maximum frequency and frequency resolution for the unit. The total time required for the pulse train is typically 100 msec. The length of the traveling wave guide and the ear canal determine the 1/4 wave length path of the unit at the desired resonant frequency. The focal length of the lens affects the length of the resonant chamber. The frequency response of the acoustic driver and microphone also must be

considered when optimizing the acoustic chamber length. The tip and instrument design are selected to give greatest sensitivity between 1,000 to 6,000 Hz with resonance falling between 1,000 to 3,500 Hz depending on the age and ear development of the subject.

For development, a system called MLSSA (Maximum-Length Sequence System Analyzer) made by DRA Laboratories or Sterling, VA was utilized. This system allows the determination of the best combination of parameters for the analysis. One setup of the system is shown on Table 1 of FIG. 3f.

Valuable response data is also available at the third and fifth octaves above the resonant frequencies stated above which provide an additional potential operational frequency range for the instrument. However, the lower frequencies have been selected since the human ear has the greatest absorption of acoustic energy in this frequency range and thus any pathology of the ear will have the greatest chance of detection due to the potential percentage change which will occur between a healthy and impaired ear.

With reference to FIG. 2 the signal generator 32, preferably a pseudo-random noise generator such as a maximum length sequence (MLS) generator, drives an acoustic driver 14 through a power amplifier 34. The MLS noise enters the acoustic chamber, formed by wave guide 16 and probe tip 18, adjacent to the lens 22 and excites the chamber which includes the ear canal 36. If there is fluid in the middle ear, acoustic energy will be reflected off the tympanum 38 and back to the lens 22. The chamber and the ear canal 36 thus form a resonant closed end tube which resonates at the $\frac{1}{2}$ wave length. At resonance, a null 180 degrees phase shift will be detected at the microphone 20 which is easy to distinguish with processing by computer 30 in software, with discrete circuitry or visually from a plot of amplitude and phase.

The output of the microphone 20 is fed to a computer 30. As noted, the computer 30 controls the MLS noise generator. It also performs cross-correlation of the original MLS noise and the output of the microphone, providing the impulse response of the total system. Using a Fast Fourier Transform (FFT) on the impulse response, amplitude and phase of the returned signal picked up by the microphone is derived for each analysis frequency. Before displaying the FFT, the amplitude and phase of the FFT may be equalized using a library of averaged response characteristics based on many subjects of similar age and ear responses with healthy ears. Thus, the output FFT should be flat in amplitude and phase for a healthy ear. If there is otitis media, a large differential response will be obtained as sound is reflected off the diseased tympanic

membrane at the resonant frequency of the system. The output can be a plot, digital listing or other suitable output which is convenient for use by the medical practitioner.

The MLS technique has a high immunity to noise interfering with the analysis. A child can cry and useful data will still be obtained. The calibration of the instrument is based on the signal achieved when using a tube of selected dimensions to represent the worst case reflection obtainable with the instrument. The minimum signal is based on the response of healthy ears as obtained from the library referred to above. Thus, the calibration of the instrument is based on repeatable response and is not arbitrarily selected as in acoustic reflection type instruments of the past.

The instrument should be designed to resonate over a narrow frequency range so that the design and construction of the instrument can be as simple as possible to reduce manufacturing costs.

FIG. 5 shows the response of the library for a group of children with similar healthy ear responses. All the responses have been averaged together and stored in the processing computer. Such techniques as using the 95 confidence limits of the averaged library data can be displayed during analysis of the data to assist the practitioner in evaluating the data.

FIG. 6 shows the response of a child with the right ear affected by otitis media. This ear shows greater reflected energy than a healthy ear but the immediate observation is less obvious than after more processing. FIG. 7 shows the dramatic improvement of the plot after the library for healthy children has been subtracted from the response as shown in FIG. 6.

Referring back to FIG. 5, the response of healthy ears for a given age range of children is shown. When using the present invention, one is able by observation or software to detect the following poor readings obtained with the instrument since the characteristic symmetrical null is not obtained:

- a. If the ear canal is not straight or if there is a blockage such as ear wax, acoustic energy will be present at frequencies just above the expected resonance of the ear.
- b. If the instrument tip is not sealed to the ear canal, there will be energy just below the characteristic response of the ear. In particular, there may be more than average low frequency energy components in the measurement.
- c. The frequency of resonance will fall within an anticipated range for given age groups and ear development. This is used as a check on the reading. For example, when a correct tip is used, the null should appear at about 2100 Hz.

An uncharacteristically high frequency at the null may indicate that the wrong tip was used.

- d. The phase response of the instrument at resonance is a very good indicator of the quality of the measurement. The steeper and the straighter the slope of the phase response, the better the measurement. A regression analysis of the phase curve may provide a measure of the slope and coefficient of variation for this purpose. This is used for detecting a poor reading of the instrument.

Thus, these problems which lead to erroneous measurements can be easily detected and corrected by taking a proper measurement.

FIG. 8 shows the response of a child suffering conductive hearing loss. This data has not had the library for healthy children subtracted from it. Notice the flat response in the range of 1,000 to 6,000 Hz where normally one would expect the characteristic null response. This data would show a dramatic positive response if the library for healthy children had been subtracted from it.

The present invention is measuring ear characteristics at only atmospheric pressure. Since the child's ear is operating at this pressure, it is the correct pressure to determine the response of the ear and potential impaired hearing problems. The present invention does not preclude conducting further investigations, and it may be desired to run a series of measurements over a differential pressure range of +200 to -200 mm for certain situations. For instance, if the ear is operating at other than atmospheric pressure due to otitis media, the tympanum can be pressure unloaded and tested. This method will aid in detailed analysis of the child's problem. The present invention may be further adapted to seal to the ear canal and pressurized to unload or load the tympanic membrane as desired. The response of the device in amplitude and phase also may be flattened, in both amplitude and phase, over the operating range of the device using standard techniques.

The wave guide design also may be used at ultrasonic frequencies into the megahertz region. The out of phase or in phase response of the ear canal and middle ear may be examined using ultrasonic frequencies to delineate features not detectable at lower frequencies, such as the delineation of air/fluid interfaces, which may provide more information to determine the pathology of the ear system.

Having now described a few embodiments of the invention, it should be apparent to those skilled in the art that the foregoing is merely illustrative and not limiting, having been presented

by way of example only. Numerous modifications and other embodiments are within the scope of one of ordinary skill in the art and are contemplated as falling within the scope of the invention as defined by the appended claims.

CLAIMS

1. An apparatus for detection of ear response comprising:
a wave guide having a proximal and distal end;
an acoustic energy source disposed substantially at the proximal end of the
5 wave guide and adapted to generate acoustic energy in response to a source
signal;
an acoustic energy detector disposed within the wave guide and adapted to
generate a reflection signal in response to detection of acoustic energy;
a probe tip disposed at the distal end of the wave guide and sized such that
10 at least a portion penetrates an ear canal;
means for generating the source signal for the acoustic energy source;
means for receiving and processing the reflected signal from said acoustic energy
detector to generate a ear response signal.
- 15 2. The apparatus of claim 1 further comprising a lens disposed at the proximal end
of said wave guide.
3. The apparatus of claim 2 further comprising a light source disposed adjacent to
the probe tip.
- 20 4. The apparatus of claim 3 wherein the probe tip is formed of a light transmissive
material.
5. The apparatus of claim 1 wherein the probe tip has a substantially tapered cross-
25 section to fit the ear canal.
6. The apparatus of claim 1 wherein the source signal further comprises pseudo-
random noise.
- 30 7. The apparatus of claim 1 further comprising a switch adapted to control the
processor.

8. The apparatus of claim 1 further comprising a housing for the wave guide, the acoustic energy source, the acoustic energy detector, the probe tip, and the processor.

9. An apparatus for detection of ear response, comprising:

5 a source of acoustic energy to apply acoustic energy to the ear;
an acoustic energy detector arranged to detect acoustic energy reflected from the ear; and

an optical path allowing viewing of the ear while the source of acoustic energy applies acoustic energy to the ear.

10

10. A probe tip for use with an acoustic reflectometer having a first end for placement within an ear canal, a second end for connection to the acoustic reflectometer and having a substantially tapered cross section.

1/14




Fig. 1

2/14




Fig. 2

3/14




Fig. 3

4/14




Fig. 3a

5/14




Fig. 3b

6/14




Fig. 3c

7/14




Fig. 3d

8/14





Fig. 3e

9/14



ACQUISITION

MODE: CROSS-CORRELATION
 LENGTH: 2048 SAMPLES (20.48)
 SAMPLE RATE: 100KHZ (10 μ SECS)
 CONCURRENT PRE-AVERAGE CYCLES: 1
 AUTORANGE: ENABLED

ANTIALIASING FILTER

TYPE: BUTTERWORTH
 BANDWIDTH: 6KHZ
 GAIN: 5 (\pm 1 VOLTS RANGE)

TRIGGER

TYPE: STIMULUS TRIGGER
 DELAY: 0 SAMPLES (0 MSEC)

UNITS

ACQUISITION: 1 VOLTS/VOLT
 STIMULUS: 1 VOLTS/VOLT

DIGITAL FILTER

CENTER: 2000HZ
 WIDTH: 4.000 OCTAVE

DIRECTORY: C:/MLSSA901

LAST SETUP FILE: C:/MLSSA901/EXP625B.SET

MODIFIED: 6-25-96 4:40 AM

STIMULUS

BURST MLS
 AMPLITUDE: \pm 0.123 VOLTS
 PERIOD: 4095 SAMPLES
 40.95 MSEC

FFT

WINDOW: RECTANGULAR
 SIZE: 2048 POINTS
 BEST RESOLUTION: 48.83
 NORMAL REFERENCE: 1
 MIN PHS ACCURACY: HIGH
 MODE: TRANSFER FUNCTION

CUMULATIVE SPECTRAL DECAY

FFTSIZE: 1024
 CYCLES: 50 (0.49 MSEC)
 WINDOW: BLACKMAN-HARRIS
 0.15 MSEC RISETIME
 RANGE: 0.000 - 15.000 KHZ
 LINEAR FREQUENCY AXIS
 6 DB/DIV, AUTO FLOOR

Fig. 3f

10/14




Fig. 4

11/14




Fig. 5

12/14




Fig. 6

13/14




Fig. 7




Fig. 8

INTERNATIONAL SEARCH REPORT

Int. l. Application No

PCT/US 97/21420

A. CLASSIFICATION OF SUBJECT MATTER
IPC 6 A61B5/12 A61B1/227

According to International Patent Classification(IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 6 A61B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	WO 83 03192 A (TEELE) 29 September 1983 see page 9, line 13 - page 13, line 12 see page 15, line 22 - page 18, line 22 see claim 21 see figures 1-3,7-9	1,9,10
A	---	8
Y	US 5 105 822 A (STEVENS ET AL.) 21 April 1992 see column 5, line 36 - column 8, line 6 see column 8, line 45 - column 9, line 4 see figures 1-1B,3,3A	1
A	---	10
	--- -/--	



Further documents are listed in the continuation of box C.



Patent family members are listed in annex.

* Special categories of cited documents :

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier document but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

- "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- "&" document member of the same patent family

Date of the actual completion of the international search

23 April 1998

Date of mailing of the international search report

06/05/1998

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Chen, A

INTERNATIONAL SEARCH REPORT

International Application No.

PCT/US 97/21420

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	GB 2 137 502 A (WELCH ALLYN INC.) 10 October 1984 see page 1, line 75 - page 2, line 121 see figures 1-5	9
A	---	1-5, 10
Y	WO 93 19670 A (MEDICAL RESEARCH COUNCIL) 14 October 1993 see page 1, line 21 - page 4, line 10 see page 5, line 7 - line 21 see figure 1	10
A	---	
A	DE 43 03 756 A (KABUSHIKI KAISHA MACHIDA SEISAKUSHO) 12 August 1993 see abstract see figure 2	3-5
A	---	
A	US 2 240 402 A (JOROSLOW) 29 April 1941 see page 1, right-hand column, line 26 - page 2, left-hand column, line 31 see figures 2-5	2-5

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 97/21420

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 8303192 A	29-09-83	US 4459996 A AU 1511483 A DE 3382619 A DK 524483 A EP 0103640 A US 4601295 A	17-07-84 24-10-83 15-10-92 16-11-83 28-03-84 22-07-86
US 5105822 A	21-04-92	NONE	
GB 2137502 A	10-10-84	US 4567881 A CA 1212755 A DE 3323794 A DK 349383 A JP 1653623 C JP 3016860 B JP 59183734 A SE 458416 B SE 8304333 A	04-02-86 14-10-86 04-10-84 01-10-84 30-03-92 06-03-91 18-10-84 03-04-89 01-10-84
WO 9319670 A	14-10-93	AT 151617 T AU 663945 B AU 3894993 A CA 2133466 A DE 69309920 D DE 69309920 T EP 0634908 A JP 7505306 T US 5546956 A	15-05-97 26-10-95 08-11-93 14-10-93 22-05-97 20-11-97 25-01-95 15-06-95 20-08-96
DE 4303756 A	12-08-93	JP 5220111 A US 5345926 A	31-08-93 13-09-94
US 2240402 A	29-04-41	NONE	